

MCB 3P 10kA C-40A 3M

Similar image (Picture shows NT304C)

Architecture

Number of protected poles	3
Number of poles	3 P
Type of pole	3 P
Fixing mode	DIN rail type O (symmetrical)
Curve	С
Functions	
Concurrently switching N-neutral	no
Connectivity	
Top connection alignement for modular devices	Aligned terminal
Bottom connection alignement for modular devices	Aligned terminal
Main electrical features	
Rated short circuit breaking capacity Icn AC according IEC60898-1	g 10 kA
Rated operational voltage Ue	415 V
Type of supply voltage	AC
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	500 V
Rated impulse withstand voltage	4000 V
Electric current	
Rated current	40 A
Rated service breaking capacity Ics AC according IEC	7,5 kA
60898-1	
min/maxi threshold value of the AC thermal operation	
Magnetic regulating currrent	5 / 10 ln
	10 kA
Rated short circuit breaking capacity Icn under 400V	TUKA
AC according IEC60898-1	
- · · ·	10 kA

Technical Dynamics	
Technical Properties Rated service breaking capacity Ics under 400V AC	7,5 kA
according IEC 60898-1	1,5 KA
Rated service breaking capacity Ics under 415V AC	7,5 kA
according IEC 60898-1	1,0 101
according inco cocosci i	
Electric current / temperature	
Rating current -25°C	50,4 A
Rating current -20°C	49,6 A
Rating current -15°C	48,7 A
Rating current -10°C	47,8 A
Rating current -5°C	46,9 A
Rating current 0°C	46 A
Rating current 5°C	45 A
Rating current 10°C	44,1 A
Rating current 15°C	43,1 A
Rating current 20°C	42,1 A
Rating current 25°C	41,1 A
Rating current 30°C	40 A
Rating current 35°C	38,9 A
Rating current 40°C	37,8 A
Rating current 45°C	36,6 A
Rating current 50°C	35,4 A
Rating current 55°C	34,2 A
Rating current 60°C	32,9 A
Rating current 65°C	31,8 A
Rating current 70°C	30,6 A
Current correction factors	
Correction factor of rating current for 2 devices placed side-by-side	11
Correction factor of rating current for 3 devices placed	l 0,95
side-by-side	
Correction factor of rating current for 4 and 5 devices	0,9
Correction factor of rating current for 4 and 5 devices placed side-by-side	
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed	
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side	l 0,85
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz	1,1
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz	1,1 1,2
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz	1,1 1,2 1,5
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz	1,1 1,2
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz	1,1 1,2 1,5
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz	1,1 1,2 1,5
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency	1,1 1,2 1,5 1
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Frequency	1,1 1,2 1,5 1
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Frequency Power	1,1 1,2 1,5 1
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Power Total power loss under IN	1,1 1,2 1,5 1 50 to 60 Hz
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance	1,1 1,2 1,5 1 50 to 60 Hz
Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Power Total power loss under IN Power loss per pole at In	1,1 1,2 1,5 1 50 to 60 Hz

_					
D	im	en	SI	0	ns

Depth of installed product	70 mm
Height of installed product	83 mm
Width of installed product	52,5 mm

Installation, mounting

Type of top connection for modular devices	with screw
Tightening torque	2,8Nm
Type of top rail clip for modular devices	NA
Type of bottom rail clip for modular devices	metallic isolated
Type of Bottom Connection for modular devices	Blconnect
Top removability for modular devices	no
Bottom removability for modular devices	no
360° product mounting position	yes

Connection

Connection cross-section of input and output with	1 / 35 mm²
screws, for massive conductors	
Connection cross section of access and exit with	1 / 25 mm²
screws, for flexible conductor	
Type of connection	with screw

Standards

Standard text	IFC 60898-1 AS/NZS 60898-1

Safety

Protection index IP	IP20	

Use conditions

Operating temperature	-25 70 °C
Degree of pollution according to IEC 60664 / IEC 60947-2	2
Class of energy limitation I2t	3
Altitude	2000 m
Air humidity protection	for all climates
Storage/transport temperature	-25 80 °C