


# Product datasheet

Specifications

**CLIPSAL**



## Flush Surround and Grid Plate, 2000 Series, 2 Gang, Vertical/ Horizontal Mount

2032VH-RD

### Main

Range of product	Series 2000
Product brand	Clipsal
Colour	Red

### Complementary

fixing mode	By screws
Material	Plastic
Marking	Without marking
Mounting position	Horizontal and vertical
Fixing center	84 mm
Length	116 mm
Width	76 mm
Depth	13 mm
Number of gangs	2 gangs
Product destination	Switch
Colour code	RD

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.9 cm
Package 1 Width	8.3 cm
Package 1 Length	12.1 cm
Package 1 Weight	56 g
Unit Type of Package 2	BB1
Number of Units in Package 2	10
Package 2 Height	13.2 cm
Package 2 Width	14.4 cm
Package 2 Length	16.6 cm
Package 2 Weight	622 g

### Contractual warranty





## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



### Environmental footprint

Total lifecycle Carbon footprint	0.5 kg CO2 eq.
Carbon footprint of the manufacturing phase [A1 to A3]	0.3 kg CO2 eq.
Carbon footprint of the distribution phase [A4]	0 kg CO2 eq.
Carbon footprint of the installation phase [A5]	0 kg CO2 eq.
Carbon footprint of the use phase [B2, B3, B4, B6]	0.1 kg CO2 eq.
Carbon footprint of the end-of-life phase [C1 to C4]	0.1 kg CO2 eq.

## Use Better



### Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Pro-active compliance (Product out of EU RoHS legal scope)
REACH Regulation	<a href="#">REACH Declaration</a>
Halogen-free status	Halogen free product
PVC free	No

## Use Longer



### Lifetime extension

Repair	No
--------	----

## Use Again



### Repack and remanufacture

End of life manual availability	No need of specific recycling operations
Take-back	No