

Product data sheet

Characteristics

MX9K108PP

New Energy Protection Kits with MAXBAR+, MAX9, 1P+N, 2 x 63A MCB, 40A RCBO, 2 x 32A MCB, NTB and Accessories



Main

Range	MAX9
Product or component type	Kit
Poles description	1P + N

Complementary

Provided equipment	<p>Miniature circuit breaker (MCB) (2) 1P 63 A 240 V AC 6000 A Interrupt Rating, kit RCBO (1) 1P + N 40 A 240 V AC 6000 A Interrupt Rating, kit Miniature circuit breaker (MCB) (2) 1P 32 A 240 V AC 6000 A Interrupt Rating, kit Terminal block (1) 1P 100 A 240 V ACKit Comb busbar (1) 1P + N 100 A 240 V ACKit Tooth cover (2) Label (1) Instruction sheet (1)</p>
--------------------	---

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	9.2 cm
Package 1 Width	11.5 cm
Package 1 Length	17.1 cm
Package 1 Weight	925.5 g
Unit Type of Package 2	BB1
Number of Units in Package 2	8
Package 2 Height	17 cm
Package 2 Width	28.2 cm
Package 2 Length	30 cm
Package 2 Weight	7.5 kg

Offer Sustainability

Sustainable offer status	Green Premium product
REACH Regulation	REACH Declaration
EU RoHS Directive	Compliant with Exemptions
China RoHS Regulation	China RoHS Declaration
RoHS exemption information	Yes

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

